

# Where in the MAXcore portal can I create a new line for the device or edit a pre-existing line?

↑ The Mon, Feb 5, 2024 
Device Settings

# Question

Where in the MAXcore portal can I create a new line for the device or edit a pre-existing line?

# Answer

This section allows a user to create a new line for the device or edit a pre-existing line.

the will remove the line from the phone.

Clicking on takes you to the **Line Information** page. When building the line for the device, select a pre-existing extension from the *extension* dropdown menu. Typing in the *Description* box will create the name that is seen under the display column. The *display* is set here (usually 4-digit extension or 10 digit phone number.) The caller name and number will be initially set to the group's default. You can also set the line keys and ring tone from this page as well.

Display	Shows the line given to the device which will be shown on the device's display screen.
Description	Name given to the device.
Caller Name	The calling line name sent to externally called parties. This is typically set to the group default.
SIP Username	Upon creation of the line, it is assigned a SIP username. This is used to track statistics and allows the device to access configuration files. This is generated automatically for the device and cannot be changed by the user or customer admin.
Extension	The assigned extension for the device.
Action	The ability to edit and delete the line are available here. Pressing the $\square$ icon will take you to the <b>Line Information</b> page which has the same options as if creating a new line. Pressing

### **Add New Line**

Clicking on will take you to the **Create Device Line** page. When building the line for the device, you select a pre-existing extension from the *extension* dropdown menu. Typing in the *Description* box will give it the name that is seen under the display column. The *display* set here (usually 4 digit extension or 10 digit phone number.) The caller name and number will be initially set to the group default. You can also set the line keys and ring tone from here as well.



## Line Information

Device *	
Polycom VVX150 ▼	
Extension *	
Please select ▼	
Description *	
Line description	
SIP Password *	
(881-)2000(198)	
Display *	
Display	
Caller Name	
Caller Name	
Caller Number *	
+12677561025	
Block Outgoing ClID	
✓ Auto Answer	
✓ Call Waiting	
Line Keys	
1 TRING Tone	
LOW_TRILL ▼	
* Required fields	
	Cancel Create

**Device** This setting defaults to the device chosen when created. This cannot be changed. **Extension** Dropdown menu to choose the extension that will be assigned to this device.

**Description** Field that typically includes the user's or location's name.

SIP Password Randomly generated authorization password unique to the device line. This cannot be

changed by the user or customer Admin.

**Display** In most cases this is the user's extension or 10-digit phone number.

Caller Name Shows the line given to the device which will be shown on the device's display screen. If left

blank it will default to the group's default external caller ID.

**Caller** The number that will display when the device makes a call.

Number

**Block** Clicking this radio box precludes the CLID from being delivered to the called party.

Outgoing CLID

Auto Answer When the handset is picked up, the call will automatically be answered and the user can begin

talking.

**Call Waiting** When activated, additional calls (>1) will ring to the device line even when the line is in use.

**Line Keys** The number of times the device line will appear on the phone.

**Ring Tone** A variety of ring tones can be selected for a line.



Online URL: https://help.maxcore.io/article-74.html