

Where in the MAXcore portal can I create a new line for the device or edit a pre-existing line?


74 Mon, Feb 5, 2024 Device Settings



Question

Where in the MAXcore portal can I create a new line for the device or edit a pre-existing line?


Answer

This section allows a user to create a new line for the device or edit a pre-existing line.

Clicking on  takes you to the **Line Information** page. When building the line for the device, select a pre-existing extension from the *extension* dropdown menu. Typing in the *Description* box will create the name that is seen under the display column. The *display* is set here (usually 4-digit extension or 10 digit phone number.) The caller name and number will be initially set to the group's default. You can also set the line keys and ring tone from this page as well.

Display	Shows the line given to the device which will be shown on the device's display screen.
Description	Name given to the device.
Caller Name	The calling line name sent to externally called parties. This is typically set to the group default.
SIP Username	Upon creation of the line, it is assigned a SIP username. This is used to track statistics and allows the device to access configuration files. This is generated automatically for the device and cannot be changed by the user or customer admin.
Extension	The assigned extension for the device.
Action	The ability to edit and delete the line are available here. Pressing the  icon will take you to the Line Information page which has the same options as if creating a new line. Pressing the  will remove the line from the phone.

Add New Line

Clicking on  will take you to the **Create Device Line** page. When building the line for the device, you select a pre-existing extension from the *extension* dropdown menu. Typing in the *Description* box will give it the name that is seen under the display column. The *display* set here (usually 4 digit extension or 10 digit phone number.) The caller name and number will be initially set to the group default. You can also set the line keys and ring tone from here as well.

Line Information

Device *

Polycom VVX150 ▼

Extension *

--Please select-- ▼

Description *

Line description

SIP Password *

12345678901234567890

Display *

Display

Caller Name

Caller Name

Caller Number *

+12677561025

☐ Block Outgoing CLID

☒ Auto Answer

☒ Call Waiting

Line Keys

1 ▼

Ring Tone

LOW_TRILL ▼

* Required fields

Cancel

Create

Device	This setting defaults to the device chosen when created. This cannot be changed.
Extension	Dropdown menu to choose the extension that will be assigned to this device.
Description	Field that typically includes the user's or location's name.
SIP Password	Randomly generated authorization password unique to the device line. This cannot be changed by the user or customer Admin.
Display	In most cases this is the user's extension or 10-digit phone number.
Caller Name	Shows the line given to the device which will be shown on the device's display screen. If left blank it will default to the group's default external caller ID.
Caller Number	The number that will display when the device makes a call.
Block Outgoing CLID	Clicking this radio box precludes the CLID from being delivered to the called party.
Auto Answer	When the handset is picked up, the call will automatically be answered and the user can begin talking.
Call Waiting	When activated, additional calls (>1) will ring to the device line even when the line is in use.
Line Keys	The number of times the device line will appear on the phone.
Ring Tone	A variety of ring tones can be selected for a line.

Online URL: <https://help.maxcore.io/article-74.html>